



LMV324

Rail-to-Rail Low Power Quad Operational Amplifiers

Description


The LMV324 is a low-power quad operational amplifier featuring rail-to-rail output swing. It is a cost-effective solution suitable for applications requiring low operating voltage, space savings, and low cost. Specifically designed for low operating voltage, the LMV324 has a minimum operating voltage of 2.1V and a maximum recommended operating voltage of 5.5V.

The LMV324 is available in SOP-14 and DIP-14 package types.


Features

- Low power consumption: 45uA/ch
- Rail-to-rail output swing
- No crossover distortion
- Supply voltage range: 2.1V to 5.5V
- Slew rate: 0.5V/us
- Gain bandwidth product: 1MHz

Package Outline Drawing



SOP-14




DIP-14

Applications

- Desktop computers
- HVAC
- Motor Control: AC induction
- Portable media players
- Professional audio mixers
- Refrigerators

Block Diagram






LMV324

Ordering Information

Type	Marking	Package
LMV324-D14	LMV324	DIP-14
LMV324-P14	LMV324	SOP-14

Pin Description

Pin Number	Pin Name	I/O	Description	
1	1OUT	O	Op-Amp 1 Output	
2	1IN-	I	Op-Amp 1 Inverting Input	
3	1IN+	I	Op-Amp 1 Non-Inverting Input	
4	VCC	P	Positive Power Supply	
5	2IN+	I	Op-Amp 2 Non-Inverting Input	
6	2IN-	I	Op-Amp 2 Inverting Input	
7	2OUT	O	Op-Amp 2 Output	
8	3OUT	O	Op-Amp 3 Output	
9	3IN-	I	Op-Amp 3 Inverting Input	
10	3IN+	I	Op-Amp 3 Non-Inverting Input	
11	GND	P	Negative Power Supply	
12	4IN+	I	Op-Amp 4 Non-Inverting Input	
13	4IN-	I	Op-Amp 4 Inverting Input	
14	4OUT	O	Op-Amp 4 Output	

Absolute Maximum Ratings (T_A=25°C unless otherwise noted)

Parameter	Symbol	Value	Unit
Supply Voltage	V _{CC}	2.1~5.5	V
Differential Input Voltage	V _{ID}	±5.5	V
Common-mode Input Voltage	V _{ICM}	-0.5~V _{CC} +0.5V	V
Maximum Operating Junction Temperature	T _J	150	°C
Operating Ambient Temperature	T _A	-20~+85	°C
Storage Temperature	T _{STG}	-65~+150	°C
Lead Temperature(Soldering , 10 s)	T _W	260	°C

Electrical Characteristics(T_A=25°C V_{CC}=2.7V unless otherwise noted)

Parameter	Symbol	Test Condition	Min	Typ	Max	Unit
Input Offset Voltage	V _{IO}		-	±0.8	±5	mV
Input Offset Current	I _{IO}		-	±10	-	nA
Input Bias Current	I _B		-	±10	-	pA



LMV324

Input Common-mode Voltage Range	V_{ICM}	$V_{CC} = 5.5V$	-0.1	-	5.6	V
Open-loop Voltage Gain	A_{OL}	$R_L=5K\Omega, V_O=0.1\sim4.9V$	70	90	-	dB
		$R_L=100K\Omega, V_O=0.035\sim4.965V$	80	94	-	dB
Common-mode Rejection Ratio	CMRR	$V_{CC}=5.5V, V_{ICM}=-0.1\sim4V$	62	90	-	dB
		$V_{CC}=5.5V, V_{ICM}=-0.1\sim5.6V$	56	88	-	dB
Power Supply Rejection Ratio	PSRR	$V_{CC}=2.5V\sim5.5V, V_{ICM}=0.5V$	60	80	-	dB
Output Voltage Swing	$V_{(OH)}$	$R_L=10K\Omega,$ Referenced to 1.35V	$V_{CC}-100$	$V_{CC}-10$	-	mV
	$V_{(OL)}$		-	80	-	
Output Short-circuit Current	I_{SC}		-	50	-	mA
Supply Current	I_{CC}		-	45	-	uA
Gain Bandwidth Product	GBWP		-	1	-	MHz
Slew Rate	S_R		-	0.5	-	V/uS

Typical Applications




Figure 1. Reference Voltage




Figure 2. Wien Bridge Oscillator




Figure 3. Hysteresis Comparator




Figure 4. Differential Amplifier



Typical Characteristics




Fig 5. Input Current Noise vs. Frequency(V_{CC}=2.7V)




Fig 6. Input Current Noise vs. Frequency(V_{CC}=5V)




Fig 7. Frequency Response vs. Resistive Load(V_{CC}=2.7V)




Fig 8. Frequency Response vs. Resistive Load(V_{CC}=5V)





Fig 9. Input Voltage Noise vs. Frequency



Package Information

SOP-14

Dimensions in mm






Symbol	Dimensions In Millimeters			Symbol	Dimensions In Millimeters		
	Min	Nom	Max		Min	Nom	Max
A	-	-	1.75	D	8.55	8.65	8.75
A1	0.10	-	0.225	E	5.80	6.00	6.20
A2	1.30	1.40	1.50	E1	3.80	3.90	4.00
A3	0.60	0.65	0.70	e	1.27 (BSC)		
b	0.39	-	0.47	h	0.25	-	0.50
b1	0.38	0.41	0.44	L	0.50	-	0.80
c	0.20	-	0.24	L1	1.05 (REF)		
c1	0.19	0.20	0.21	θ	0°	-	8°



Package Information

DIP-14

Dimensions in mm



Symbol	Dimensions In Millimeters			Symbol	Dimensions In Millimeters		
	Min	Nom	Max		Min	Nom	Max
A	3.75	3.81	3.95	E1	7.35	7.62	7.85
A1	0.51	-	-	e	2.54 (BSC)		
A2	3.20	3.30	3.45	L	3.00	3.30	3.60
B	0.38	0.48	0.56	E2	8.00	8.40	8.80
B1	1.52 (BSC)			θ1	9°	-	15°
C	0.20	0.25	0.34	θ2	7°	-	13°
D	18.80	19.05	19.30	θ3	8°	-	14°
E	6.20	6.35	6.50	θ4	5°	-	12°



Shikues Disclaimer

1.Accuracy of Information and Right to Modify

The information provided in this document is for reference only. Shikues reserves the right to make changes to this document and to the specifications of the products described herein at any time, without prior notice, for the purpose of improving reliability, function, design, or for any other reason. It is the customer's responsibility to obtain and verify the latest product information and specifications before making any final design, procurement, or usage decisions.

2.No Warranty

Shikues makes no express or implied warranties, representations, or guarantees regarding the suitability of its products for any particular purpose.

Shikues assumes no liability for any assistance provided or for the design of customer products. All products are supplied "as is."

3.Intended Use and Limitation of Liability

The products described in this document are intended for use in general-purpose electronic devices. They are neither designed nor tested nor authorized for use in transportation equipment or applications requiring high reliability. Unless expressly authorized in writing by Shikues, these products must not be used as critical components in life-support systems or any applications where failure could directly pose a risk to human life (including, but not limited to, medical devices, transportation systems, aerospace equipment, nuclear facilities, and safety-critical systems).

Shikues assumes no responsibility or liability for any consequences arising from the use of its products in unauthorized or unintended applications.

Neither Shikues nor its representatives shall be held liable for any resulting damages.

4.Intellectual Property

This document does not grant any express or implied license—whether by estoppel, implication, or otherwise—to use any intellectual property rights of Shikues.